

## PT-1 - PIPO TIMER TIME TABLE

DESIRED TIME (ON or OFF)	DIP SWITCHES (X = closed)							
To set the 'ON Time', use the 'ON' DIP switches on the Left. To set the 'OFF Time', use the 'OFF' DIP switches on the Right.	ON1 OFF1	ON2 OFF2	ON3 OFF3	ON4 OFF4	ON5 OFF5	ON6 OFF6	ON7 OFF7	ON8 OFF8
	1sec	2sec	4sec	8sec	16sec	x10	÷10	÷100
If DIP Switches 'ON7' and 'ON8' are in the closed position, the ON and OFF Time will be controlled by the corresponding potentiometers, with range from 100mS to 10sec.							X	X
0 mS = 0.00 sec = 0.00 min								
10 mS = 0.01 sec = 0.00 min	X							X
20 mS = 0.02 sec = 0.00 min		X						X
30 mS = 0.03 sec = 0.00 min	X	X						X
40 mS = 0.04 sec = 0.00 min			X					X
50 mS = 0.05 sec = 0.00 min	X		X					X
60 mS = 0.06 sec = 0.00 min		X	X					X
70 mS = 0.07 sec = 0.00 min	X	X	X					X
80 mS = 0.08 sec = 0.00 min				X				X
90 mS = 0.09 sec = 0.00 min	X			X				X
100 mS = 0.10 sec = 0.00 min		X		X				X
110 mS = 0.11 sec = 0.00 min	X	X		X				X
120 mS = 0.12 sec = 0.00 min			X	X				X
130 mS = 0.13 sec = 0.00 min	X		X	X				X
140 mS = 0.14 sec = 0.00 min		X	X	X				X
150 mS = 0.15 sec = 0.00 min	X	X	X	X				X
160 mS = 0.16 sec = 0.00 min					X			X
170 mS = 0.17 sec = 0.00 min	X				X			X
180 mS = 0.18 sec = 0.00 min		X			X			X
190 mS = 0.19 sec = 0.00 min	X	X			X			X
200 mS = 0.20 sec = 0.00 min			X		X			X
210 mS = 0.21 sec = 0.00 min	X		X		X			X
220 mS = 0.22 sec = 0.00 min		X	X		X			X
230 mS = 0.23 sec = 0.00 min	X	X	X		X			X
240 mS = 0.24 sec = 0.00 min				X	X			X
250 mS = 0.25 sec = 0.00 min	X			X	X			X
260 mS = 0.26 sec = 0.00 min		X		X	X			X
270 mS = 0.27 sec = 0.00 min	X	X		X	X			X
280 mS = 0.28 sec = 0.00 min			X	X	X			X
290 mS = 0.29 sec = 0.00 min	X		X	X	X			X
300 mS = 0.30 sec = 0.01 min		X	X	X	X			X
400 mS = 0.40 sec = 0.01 min			X				X	
500 mS = 0.50 sec = 0.01 min	X		X				X	
600 mS = 0.60 sec = 0.01 min		X	X				X	
700 mS = 0.70 sec = 0.01 min	X	X	X				X	
800 mS = 0.80 sec = 0.01 min				X			X	
900 mS = 0.90 sec = 0.02 min	X			X			X	
1000 mS = 1.00 sec = 0.02 min		X		X			X	
1100 mS = 1.10 sec = 0.02 min	X	X		X			X	
1200 mS = 1.20 sec = 0.02 min			X	X			X	

## PT-1 - PIPO TIMER TIME TABLE

DESIRED TIME (ON or OFF)				DIP SWITCHES (X = closed)							
To set the 'ON Time', use the 'ON' DIP switches on the Left. To set the 'OFF Time', use the 'OFF' DIP switches on the Right.				ON1 OFF1	ON2 OFF2	ON3 OFF3	ON4 OFF4	ON5 OFF5	ON6 OFF6	ON7 OFF7	ON8 OFF8
				1sec	2sec	4sec	8sec	16sec	x10	÷10	÷100
1300 mS = 1.30 sec = 0.02 min	X		X	X				X			
1400 mS = 1.40 sec = 0.02 min		X	X	X				X			
1500 mS = 1.50 sec = 0.03 min	X	X	X	X				X			
1600 mS = 1.60 sec = 0.03 min					X			X			
1700 mS = 1.70 sec = 0.03 min	X				X			X			
1800 mS = 1.80 sec = 0.03 min		X			X			X			
1900 mS = 1.90 sec = 0.03 min	X	X			X			X			
2000 mS = 2.00 sec = 0.03 min			X		X			X			
2100 mS = 2.10 sec = 0.04 min	X		X		X			X			
2200 mS = 2.20 sec = 0.04 min		X	X		X			X			
2300 mS = 2.30 sec = 0.04 min	X	X	X		X			X			
2400 mS = 2.40 sec = 0.04 min				X	X			X			
2500 mS = 2.50 sec = 0.04 min	X			X	X			X			
2600 mS = 2.60 sec = 0.04 min		X		X	X			X			
2700 mS = 2.70 sec = 0.05 min	X	X		X	X			X			
2800 mS = 2.80 sec = 0.05 min			X	X	X			X			
2900 mS = 2.90 sec = 0.05 min	X		X	X	X			X			
3000 mS = 3.00 sec = 0.05 min		X	X	X	X			X			
4000 mS = 4.00 sec = 0.07 min			X								
5000 mS = 5.00 sec = 0.08 min	X		X								
6000 mS = 6.00 sec = 0.10 min		X	X								
7000 mS = 7.00 sec = 0.12 min	X	X	X								
8000 mS = 8.00 sec = 0.13 min				X							
9000 mS = 9.00 sec = 0.15 min	X			X							
10000 mS = 10.00 sec = 0.17 min		X		X							
11000 mS = 11.00 sec = 0.18 min	X	X		X							
12000 mS = 12.00 sec = 0.20 min			X	X							
13000 mS = 13.00 sec = 0.22 min	X		X	X							
14000 mS = 14.00 sec = 0.23 min		X	X	X							
15000 mS = 15.00 sec = 0.25 min	X	X	X	X							
16000 mS = 16.00 sec = 0.27 min					X						
17000 mS = 17.00 sec = 0.28 min	X				X						
18000 mS = 18.00 sec = 0.30 min		X			X						
19000 mS = 19.00 sec = 0.32 min	X	X			X						
20000 mS = 20.00 sec = 0.33 min			X		X						
21000 mS = 21.00 sec = 0.35 min	X		X		X						
22000 mS = 22.00 sec = 0.37 min		X	X		X						
23000 mS = 23.00 sec = 0.38 min	X	X	X		X						
24000 mS = 24.00 sec = 0.40 min				X	X						
25000 mS = 25.00 sec = 0.42 min	X			X	X						
26000 mS = 26.00 sec = 0.43 min		X		X	X						
27000 mS = 27.00 sec = 0.45 min	X	X		X	X						
28000 mS = 28.00 sec = 0.47 min			X	X	X						

## PT-1 - PIPO TIMER TIME TABLE

DESIRED TIME (ON or OFF)	DIP SWITCHES (X = closed)							
To set the 'ON Time', use the 'ON' DIP switches on the Left. To set the 'OFF Time', use the 'OFF' DIP switches on the Right.	ON1 OFF1	ON2 OFF2	ON3 OFF3	ON4 OFF4	ON5 OFF5	ON6 OFF6	ON7 OFF7	ON8 OFF8
	1sec	2sec	4sec	8sec	16sec	x10	÷10	÷100
29000 mS = 29.00 sec = 0.48 min	X		X	X	X			
30000 mS = 30.00 sec = 0.50 min		X	X	X	X			
40000 mS = 40.00 sec = 0.67 min			X			X		
50000 mS = 50.00 sec = 0.83 min	X		X			X		
60000 mS = 60.00 sec = 1.00 min		X	X			X		
70000 mS = 70.00 sec = 1.17 min	X	X	X			X		
80000 mS = 80.00 sec = 1.33 min				X		X		
90000 mS = 90.00 sec = 1.50 min	X			X		X		
100000 mS = 100.00 sec = 1.67 min		X		X		X		
110000 mS = 110.00 sec = 1.83 min	X	X		X		X		
120000 mS = 120.00 sec = 2.00 min			X	X		X		
130000 mS = 130.00 sec = 2.17 min	X		X	X		X		
140000 mS = 140.00 sec = 2.33 min		X	X	X		X		
150000 mS = 150.00 sec = 2.50 min	X	X	X	X		X		
160000 mS = 160.00 sec = 2.67 min					X	X		
170000 mS = 170.00 sec = 2.83 min	X				X	X		
180000 mS = 180.00 sec = 3.00 min		X			X	X		
190000 mS = 190.00 sec = 3.17 min	X	X			X	X		
200000 mS = 200.00 sec = 3.33 min			X		X	X		
210000 mS = 210.00 sec = 3.50 min	X		X		X	X		
220000 mS = 220.00 sec = 3.67 min		X	X		X	X		
230000 mS = 230.00 sec = 3.83 min	X	X	X		X	X		
240000 mS = 240.00 sec = 4.00 min				X	X	X		
250000 mS = 250.00 sec = 4.17 min	X			X	X	X		
260000 mS = 260.00 sec = 4.33 min		X		X	X	X		
270000 mS = 270.00 sec = 4.50 min	X	X		X	X	X		
280000 mS = 280.00 sec = 4.67 min			X	X	X	X		
290000 mS = 290.00 sec = 4.83 min	X		X	X	X	X		
300000 mS = 300.00 sec = 5.00 min		X	X	X	X	X		